



PROFESSIONAL LINE

PRODUCT INFORMATION BULLETIN

Date: August 26, 2014
Number: 7231
Division: Genie®
Product Family: Commercial Operators
Product Series: Accessories
To: All Genie Professional Line Wholesalers, Dealers and Installers
Re: Transmitter and Receiver Compatibility


Please review the following charts on the following pages for compatibility of the commercial receivers with both commercial and residential transmitters.


These charts are a guide, for any detailed questions please contact Commercial Technical Service at 800-843-4084, option 4.


Commercial Transmitters

Commercial Receivers

						
GIDFX1.S One Button Intellicode 315 MHz Transmitter	GIDFX2.S Two Button Intellicode 315 MHz Transmitter	GIDFX3.S Three Button Intellicode 315 MHz Transmitter	GIDFX4.S Four Button Intellicode 315 MHz Transmitter	GIDFX5.S Open/Close/Stop Intellicode 315 MHz Transmitter	37344R GenieMaster Transmitter Supports Intellicode 315/390 MHz & Fixed Code	37224R Intellicode 315/390 MHz Keypad Wireless Keyless Entry Pad






 36163R Intellicode 315/390 MHz External Receiver	One GIDFX1.S One Button Intellicode Transmitter & one 36163R receiver will operate 1 Door <hr/> Maximum of 23 Transmitters allowed per receiver.	One GIDFX2.S Two Button Intellicode Transmitter & Two 36163R receivers will operate 2 Doors <hr/> Maximum of 23 Transmitters allowed per receiver.	One GIDFX3.S Three Button Intellicode Transmitter & Three 36163R receivers will operate 3 Doors <hr/> Maximum of 23 Transmitters allowed per receiver.	One GIDFX4.S Four Button Intellicode Transmitter & Four 36163R receivers will operate 4 Doors <hr/> Maximum of 23 Transmitters allowed per receiver.	Not Compatible	One 37344R GenieMaster Intellicode 315/390 MHz & Fixed Code Transmitter & Three 36163R receivers will operate 3 Doors <hr/> Maximum of 23 Transmitters allowed per receiver.	One 37224R Intellicode 315/390 MHz Keypad & Three 36163R receivers will operate 3 Doors <hr/> Maximum of 23 Transmitters allowed per receiver.
---	--	--	--	--	----------------	--	--


 34564R Fixed Code 390 MHz 3 Wire Fixed Code 9 Switch Trinary External Receiver For use with GenieMaster Transmitter	Not Compatible	Not Compatible	Not Compatible	Not Compatible	Not Compatible	One 37344R GenieMaster Intellicode 315/390 MHz & Fixed Code Transmitter wand Three 34564R receivers will operate 3 Doors <hr/> Unlimited # Transmitters allowed per receiver.	Not Compatible
--	----------------	----------------	----------------	----------------	----------------	--	----------------


 Internal Receiver 111397.0001.S 315 MHz Internal Intellicode Receiver Standard on GCL-T/J/H/GT/GH Option on GCL-MT/MJ/MH	One GIDFX1.S One Button Intellicode Transmitter & One 111397.0001.S internal receiver will operate 1 Door <hr/> Maximum of 50 Transmitters allowed per receiver.	One GIDFX2.S Two Button Intellicode Transmitter & Two 111397.0001.S internal receivers will operate 2 Doors <hr/> Maximum of 50 Transmitters allowed per receiver.	One GIDFX3.S Three Button Intellicode Transmitter & Three 111397.0001.S internal receivers will operate 3 Doors <hr/> Maximum of 50 Transmitters allowed per receiver.	One GIDFX4.S Four Button Intellicode Transmitter & Four 111397.0001.S internal receivers will operate 4 Doors <hr/> Maximum of 50 Transmitters allowed per receiver.	One GIDFX5.S Open/Close/Stop Intellicode Transmitter & One 111397.0001.S internal receiver will operate 1 Door <hr/> Maximum of 50 Transmitters allowed per receiver.	One 37344R GenieMaster Intellicode 315/390 MHz & Fixed Code Transmitter & Three 111397.0001.S internal receivers will operate 3 Doors <hr/> Maximum of 50 Transmitters allowed per receiver.	One 37224R Intellicode 315/390 MHz Keypad & Three 111397.0001.S internal receivers will operate 3 Doors <hr/> Maximum of 50 Transmitters allowed per receiver.
---	--	--	--	--	---	--	--


Residential Transmitters

Commercial Receivers

				
G3T-BX 37218R Three Button Intellicode Transmitter	G1T 38501R One Button Intellicode Transmitter	G1TR-3 37517S Three Button Intellicode Transmitter	GM3T-BX 37344R GenieMaster Transmitter Supports Intellicode 315/390 MHz & Fixed Code	37224R Intellicode 315/390 MHz Keypad Wireless Keyless Entry Pad

 36163R Intellicode 315/390 MHz External Receiver	One 37218R Three Button Intellicode Transmitter & Three 36163R receivers will operate 3 Doors Maximum of 23 Transmitters allowed per receiver.	One 38501R One Button Intellicode Transmitter & One 36163R receiver will operate 1 Doors Maximum of 23 Transmitters allowed per receiver.	One 37517S Three Button Intellicode Transmitter [†] & Three 36163R receivers will operate 3 Doors Maximum of 23 Transmitters allowed per receiver.	One 37344R GenieMaster Intellicode 315/390 MHz/Fixed Code Transmitter & Three 36163R receivers will operate 3 Doors Maximum of 23 Transmitters allowed per receiver.	One 37224R Intellicode 315/390 MHz Keypad & Three 36163R receivers will operate 3 Doors Maximum of 23 Transmitters allowed per receiver.
--	---	--	--	--	---

 34564R Fixed Code 390 MHz 3 Wire Fixed Code 9 Switch Trinary External Receiver For use with GenieMaster Transmitter	Not Compatible	Not Compatible	Not Compatible	One 37344R GenieMaster Intellicode 315/390 MHz/Fixed Code Transmitter will operate an unlimited # of 34564R receivers with same switch setting. Unlimited Transmitters allowed per receiver.	Not Compatible
---	-------------------	-------------------	-------------------	---	-------------------

 Internal Receiver 111397.0001.S 315 MHz Internal Intellicode Receiver Standard on GCL-T/J/H/GT/GH Option on GCL-MT/MJ/MH	One 37218R Three Button Intellicode Transmitter & Three 111397.0001.S internal receivers will operate 3 Doors Maximum of 50 Transmitters allowed per receiver.	One 38501R One Button Intellicode Transmitter & One 111397.0001.S internal receiver will operate 1 Doors Maximum of 50 Transmitters allowed per receiver.	Not Compatible	One 37344R GenieMaster Intellicode 315/390 MHz/Fixed Code Transmitter & Three 111397.0001.S internal receivers will operate 3 Doors Maximum of 50 Transmitters allowed per receiver.	One 37224R Intellicode 315/390 MHz Keypad & Three 111397.0001.S internal receivers will operate 3 Doors Maximum of 50 Transmitters allowed per receiver.
--	---	--	-------------------	---	--

[†] Longer duration button press may be required to prevent multiple button presses due to single frequency transmitter